

ROBBY MANUAL

Plug and Play Network Camera (P2P) Easy User Manual



For more information, please visit the online CD website:
<http://www.netcam360.com>

USER GUIDE

1. Connect IP camera to power

- 1). Connect the camera to power by power adapter;
- 2). Waiting for 30 seconds until you hear a sound prompting up "Welcome to use". The camera is ready for use.

2. Install client software

- 1) Connect your phone to internet (Wi-Fi/3G/4G);
- 2). Phones with Android system can either scan the QR code or visit www.netcam360.com to download and install the software .
- 3). Phones with Apple system can search "netcam" in the APP store, then download and install the software.




3. AP (access point) to IP camera (take Android phones for example):

- 1). Enter WLAN (WIFI) setting in the phone, search for IPC's SSID. See Picture (1);
- 2). Click IPC SSID , input password '0123456789' ,The phone and camera is connected. See Picture (2);




Picture (1)



Picture (2)

3).From the phoneClick  , Click  Add device add device , See Picture (3)



Picture (3)

4) . Click "Search device in Lan".See Picutre(4).




Picture (4)

5) .Click on device's ID number (usually starts with HSL or XLT), then clickon "done". Your IP camera is now online. See Picture (5).




picture (5)



4. IP camera's WIFI settings

1) .Chlick on the setting icon , See picture (6) .



picture (6)

2).Click "WIFI-Setting" , See Picture (7) .




Picture (7)

3).Click "WIFI Manage" ,See Picture (8) .



Picture (8)

4).Choose the SSID you want to add to, put password, click"done". IP camera will restart automatically, then auto connect to house WIFI. See Picture (9).



Picture (9)

5. Watch video(below image is taken from mobile phone view. IE,PC, Padsare all supported).



6. Other ways to connect

- 1). Web (IE browser): After the IPC is connected to local WIFI,use IP Scanner to search for the IP camera. Double click the IP address and open with IE, and view the video. You need to install the IE plug-in for the first time.
- 2). PC client: install the PC client software, add devices (add a device ID or IP address), then view the camera videos.

Remark:

Users for the first time, be it PC, Web, Android phones or tablets, Apple phones or tablets, make sure you install the corresponding software.



Android APP



IOS APP

HD WIFI IP Camera&Carcorder

Multi-use smart home security product

Features :

- ※ A multi-use crossover product with latest HD and wireless transmission solution;
- ※ Fashion cartoon adorable pet modeling, custom for smart home security;
- ※ High definition video images, resolution 1280*960, 1.3MP;
- ※ Configured 2MP Industrial-grade high-definition lens;
- ※ Using ICR dual filter switch, images looks more realistic,quality always maintain best performance in different light environment;
- ※ Internal 8pcs TYNTEK infrared lights, effectively improve night vision clarity, low power consumption, long service life;
- ※ Camera has strong magnetic body and 360 degrees rotation angle, strong magnetic base can be directly adsorbed on metal objects;
- ※ HD video and audio transmission, support live two-way pronunciation, intelligent noise reduction, clear sound pick-up;
- ※ Using latest WIFI technology, signal transmission is stable and reliable in the wireless environment;
- ※ Support Max. 64Gb TF card memory and remote video playback; Can set loop-cycle recording or motion detection recording;
- ※ The camera comes with AP hotspot, search and connect directly through the mobile phone APP; It can be fixed on the car dashboard and used as carcorder;
- ※ Direct AP function contributed to more extensive use of the camera;
- ※ Supplied power by universal Android mobile data line or power bank;
- ※ Mobile phone APP: NETCAM, please download and install in the Application Market.All functions can be set through the APP;
- ※ APP has Chinese and English versions, humanized interface design,easy to use, support four-screen display at the same time;
- ※ Home products design, industrial products standards, all products passed aging test, stable and reliable performance;



Application :

Home security protection, care for the elderly, children and pets. Shops security protection, enjoy life. Hospital patient care, real-time voice intercom. Car protection, carcorder, prevent racketeer.

| Specification | |
|-------------------|----------------------------------------------------|
| Image Sensor | 1. 3MP CMOS |
| Min. illumination | Color 0.6 Lux@F1.2, B/W 0.08 Lux@F1.2, 0 Lux IR on |
| Day/Night | IR-CUT dual optical filter |
| Lens | Megapixel HD lens |
| S/N Ratio | ≥ 50dB |
| Gain Control | Manual / Auto |
| White Balance | Manual / Auto |
| Electric Shutter | 1/25-1/100, 000s |
| Video Compression | H.264, dual-stream |
| Video Mode | High Definition / Standard Definition / Fluency |
| Max. Image Size | Main stream 1280×960 ; Sub Stream 640×480; |
| Image Mirroring | 180degree flip mirroring |
| Frame Rate | 1-25fps adjustable |
| Wireless Network | WIFI 802.11b/g/n |
| Protocol | FTP/PPPOE/DHCP/DDNS/NTP/UPnP |
| Intelligent Alarm | Motion detection |
| Audio Input | Internal MIC |
| Audio Output | Internal Loudspeaker |
| Audio Compression | AAC |
| Memory | Micro SD card |
| Restore Defaults | One-key Restore Defaults Settings |
| IR Lights | 8pcs TYNTEK IR lights |
| IR Distance | 《5M |
| Power Supply | DC5V/1A |
| Work Environment | Temperature -10°C~+50°C, Humidity ≤90% |