

Recorder Instruction Manual

Please read the manual before using it.

Statement:

- 1. First, thanks for using our company's digital products!
- 2. Please read the manual before using for the proper use of it.
- 3. As for the information, please back up on your own. Our company takes no responsibility to any loss of data caused by abnormal operation of software, hardware, or product repair, or battery changing, or other accidents, also the loss caused indirectly by these reasons. Meanwhile, we also can't control the possible misunderstanding of the manual from the customer. Thus, our company won't take charge of accidental damage caused by using this manual, also the third party's claim for compensation caused by using this manual. (The product system will occur some part of the memory, so it's normal if there's any difference with the standard memory)


Note:


- 1. Please do not attempt to open, repair or modify the product.
- 2. Please do not use this product in the region with prohibited use sign of electronic products (such as airplane, etc).
- 3. Please do not put in the mouth of products or accessories.
- 4. Please do put the product into water or other liquids.
- 5. Please do not use this product in special cold, hot, humid or dusty environments.

Warnings:

- 1. Please do not drop the product itself or its parts, for avoiding malfunctions.
- 2. Please do not keep the product under the bright light, or heat, for extending the life span of the product itself.

- 3. Please charge it sometimes if leave it unused for a long period, to avoid losing battery function.
- 4. In order to expand the life span of the battery, please don't use it when charging.
- 5. Please do not force to remove or waggle up and down, side to side to connect accessories (For example: headphone, microphone, USB connection, etc.).
- 6. This machine is for learning tool, our company will out of any law responsibility caused by the economical or







commercial usage.

- 7. Please don't set it under 60° C environment (such as: sauna room, inside the packed car), it might reach to 80° C inside the car.
- 8. Our company takes no responsibility to any loss of data when using the product or service. So if there is important information in the product memory, please back up on your own.
- 9. Please note that this product is prohibited for illegal use. For example: for the privacy of others or eavesdropping.

Product description of each part:

1: DEL/A-B	7: Hole for hang	ing 13: Inner
microphone		
2: Vol	8: Earphone [₩] jack	14: Menu key
3: Vol	9: Record [₩] lamp	15: Play
4: USB jack	10: ^{▶▶} Screen	16: Play
5: Microphone jack	11: Stop key	17: Power key
6: Record key	12: Play/Pause	

The basic application method:

-14

15

16

-17

Main function section



Play record System setting Play music

Special button operation specification

In the manual, "short press" "long press" appear frequently, their meanings as follows:

- 1. Short press: After pressing the button, then leave the finger immediately.
- 2. Long press: After pressing the button, keep it for a while , until the screen with related contents.

The basic application method

• Turn on the power

- 1. Check the inner lithium battery enough or not.
- 2. Set the "ON", after initialization, the screen with "play record interface"

Turn off the power

- 1. When the machine is in standby mode, set to "OFF", then the machine turned off;
- 2. When the machine is in the stop state, press the "Play" button for a few seconds, the machine shutdowns after showing "Bye-Bye", which can only turn off the working state, can't turn off the power. If no use in a long period, please turn off the power "OFF", which could save power.
- 3. During record, if the battery is going to use up, then it will shutdown automatically.

%Suggestion: Please stop the machine by "PLAY/PAUSE" , then turn off the power by "OFF". If turn off the power directly, it will reset to defaults.

• Record

- 1. Start to record : Turn on the power, machine came into record interface, short press the "REC" to enter default state, when the record lamp in a long flash, and the data in the upper screen start to change, which means the record state.
- 2. **Pause record :** During record, short press "REC" for pausing record, lamp and the data in the upper screen flash, cancel pausing, then short press again the "REC".
- 3. Save record : During record process, short press "Pause" button, "Save" appears on the screen. Enter into play/ standby mode. Repress "PLAY" button, will play current record file.
- 4. Turn off record lamp : During record process, short press "Menu M" to turn off record lamp, then short press again "Menu M" to turn on record lamp.

• Play/ Pause



Under working interface, short press "Play" or "Play" to choose play record or play music. Short

press "Menu M" to enter play interface, short press "Play" to start play, then short press again "Play" to pause/play.

• Change playing content



Under play state, short press "Play" or "Play" button to

change playing content.

• Change music file/record file mode



Under playing music file or record file state, short press "Menu M" to exit to main menu, short press "Play" or

"Play" to choose voice play or music play, short press "Play" for playing confirmation.

Adjust volume




Under playing music file or record file state, short press "Volume" button, then will show the volume degree, press "Volume+" to increase volume, press "Volume-" to decrease volume, and there'll be volume respond on the screen. After adjustment, short press "Play" to save the volume and exit the volume adjustment mode. (It'll exit automatically if there's no operation in 10 seconds.)

 Choose play and play, Fast forward, Rewind



Under

playing music file or record file state, short press "Play" or "Play" to choose the next play file, long press "Play" or "Play" to fast forward, rewind.



When playing record/music file, short press "DEL/A-B" to set repeat starting point A, then short press "DEL/A-B" to set repeat ending point B. There'll be "A-B" in screen, repress shortly "DEL/A-B" to repeat the content between A-B, then short press "DEL/A-B" to exit "A-B" repeat mode. (Default: It back to normal playing after repeating five times)

- Delete file
- Delete file : At the music / record playing standby or pause



interface, short press "DEL/A-B" to choose delete, short press "Play" or "Play" to choose delete single file/ whole file, exit, then short press "Menu M" to confirm delete, then "deleting" showed on the screen.



XWarning: "Delete all" means to delete forever, the file can't be back, please be cautious.

Set to play



Under playing mode, short press "Menu M" to set the playing menu (cycle

mode, sound effect mode, repeat mode, repeat time, repeat interval, exit), short press "Play" or "Play" to choose as follows:

1. Cycle mode: Short
press "Menu M"
to enter cycle
mode, short press
"Play" or
"Play" to



operate. (normal mode, single mode, full mode, exit), short press "Play" or "Menu M" to confirm and exit the playing interface.

2. Sound effect mode: Short press "Menu M" to enter sound



effect mode, short press "Play" or "Play" to operate (nature, rock, pop, classic, soft, jazz, mega bass), short press "Play" or "Play" to confirm and exit the playing interface.

- 3. Repeat mode: Short press "Menu M" to set the repeat start A, repress shortly "DEL/A-B" to set repeat end B, There' 11 be "A-B" in screen, repress shortly "DEL/A-B" to repeat the content between A-B, then short press "DEL/A-B" to exit "A-B" repeat mode. (Default: It back to normal playing after repeating five times)
- 4. Repeat time: Short press "Menu M" to set repeat time, short press "Play" or



"Play" to choose time (0-10), short press "Play" or "Menu M" to confirm and exit the playing interface.

5. Repeat interval:

Short press "Menu M" to set repeat interval, short press "Play" or



"Play" to choose time (0-10), short press "Play" or "Menu M" to confirm and exit the playing interface.

• System setting



Under power on interface, short press "Please press / to input

code", short press "Menu" to enter next code setting, choose system setting, short press "Menu" to enter system setting, short press "Play" or "Play" to choose as follows

1. System time: Short press "Menu M" to enter time



setting interface, short press "Vol" or "Vol" to operate (vear/month/day/hour/minute/second), short press "Play" or "Play" to set those accordingly, then short press "Menu M" to confirm and exit the playing interface.

2. Repeat type : Short press "Menu Μ" to repeat enter



type, short press "Play" or "Play" to choose (highquality recordings HQ 192Kbps , high-quality sound control192Kbps VOR, long-time recording32Kbps, long-time voice control 32Kbps VOR, high-fidelity recording SHQ 384VOR, then short press "Menu M" to confirm and exit to menu setting.

3. Recording

> origin Short : "Menu M" press to enter



recording origin, short press "Play" or "Play" to choose (microphone, input music, exit), short press "Menu M" to confirm and exit to menu setting.

4. Monitor switch : Short1v press M" "Menu to monitor enter



switch, short press "Play" or "Play" to choose (Open / close monitor), short press "Menu M" to confirm and exit

to menu setting.

setting.

Short1y

"Menu

6. Language

5. Backlight time : Short1v press M" "Menu to backlight enter time setting, short press

choice :

М"

press



"Play" (0-29) to

"Play" to choose

this enter "Play" or interface, short press language, then short press "Menu M" confirm and exit to menu setting.

:

to

press

to

7. Shut down setting: Shortly "Menu M" press to enter this



interface, short press "Play" or "Play" to choose (Power saving mode. Sleep mode), short press "Menu M" to enter, short press "Play" or "Play" to adjust time, short press "Menu M" to confirm and exit to menu setting.

Comparing 8. adjustment Short1y Μ"

"Menu



enter interface, short press "Play" or "Play" to choose comparing light (01-15), short press "Menu M" confirm and exit to menu setting. The lighter of the comparing light, the brighter of the screen.


Storage situation: Shortly press "Menu M" to enter 9. interface, you can check the total space and the used space of the machine. Short press "Menu M" to confirm and exit to menu setting.

- 10. Firmware version: Shortly press "Menu M" to check machine software information. Short press "Menu M" to confirm and exit to menu setting.
- 11. Button sound • Short1v press М" "Menu to interface. enter

short press "Play" or "Play" to adjust (01-30). Short press "Menu M" to confirm and exit to menu setting.

LINE-IN wire recording setting


- 1. To choose music input or to connect (CD player, Recorder, DVD) through LINE-IN port, then press the recording button to record.
- 2. External microphone recording: After connecting an external microphone through LINE-IN interface, and use it by the same way as using built-in microphone.
- 3. **Telephone recording:** After connecting a telephone box by LINE-IN interface, and use it as the same as using the built-in microphone (in general). (Figure 1)





Connecting with computer

- Connect one port of USB to itself, the other one connect 1. with computer USB.
- Remove the removable disk properly to avoid missing data. 2.
- 3. When connecting with computer, it can be used as U-disk. You can upload/download favorite music file or other file by copy. During transfer the data, can't stop the connection, or it would lead missing data.



- Charge
- Connect one port of USB with itself, the other one connect 1.

with computer USB. 4 hours can fully charged it, and it will show full of the battery mark (Please turn on the switch during charging). This machine power is provided by charging battery. During charge, the charging mark will show on the screen, which won't flicker when fully charged.

2. The battery be charged also



discharged, for durable usage of battery. When it shows only one grid power, please charge timely, not charge until use

Item		Specification				
Space		4GB	8GB	16GB	32GB	
32Kbps		280Hr	560Hr	1120Hr	2240Hr	
192Kbps		48Hr	96Hr	192Hr	384Hr	
384Kbps		24Hr	48Hr	96Hr	192Hr	
File quantity		199 pcs				
Recording type		WAV type				
Sampling frequency		16KHz-48KHz				
Frequency		24MHz				
Recording power		7mA-12mA				
Actual maximum output		L) 9mW+(R) 9mW (320hm)				
External	Micro	phone	3.5pie Stereo jack			
l input	Headpl	hone	3.5pie Stereo jack			
USB			PC Interface USB1.1/USB2.0 FULL Speed			
Inner microphone output		800mW				
Inner microphone		Dynamic 26mm, 80hm				
Inner MIC		Non-oriented capacitor microphone				
S/N(Noise ratio)		90dB				
Power; rated voltage		Lithium battery (230MA) : 3.6V-4.2V				
USB input 1	rated		5V300MAH-5V500MAH			
voltage/power						
Storage		Inserted flash memory				
Operation temperature		-20°C~60°C				
Weight		About 33g				
Size		85 mm $\times 36$ mm $\times 14$ mm				
Battery life		Record	21 hours			
(The powe		Play	8 hours (H	oy earphone	e)	
charging	fully					
one time)						

up power.

Technology Specification

Difficulty Solution

Problem	Cause	Solutions	
No showing	Low battery;	Timely charge;	
of the LCD	Check the power on or	Turn on the power;	
	off;		
	Not in the recording	Turn to recording state;	
Recording	state;	Timely charge;	
stop	Low battery;	Delete some files or move	
working	Memory capacity has	them to an external device;	
	been raised to the		
	limit or full		
	recording mode;		
Unable to	Low battery;	Timely charge;	
open audio	No audio file;	Confirm documents;	
files	The minimum volume;	Adjust the volume;	
Words on	The language	Choose correct language	
the screen	selection correctness		
are			
abnormal			
	Confirm that there is	Remove the headset;	
No sound	earphone;	Adjust the volume;	
from the	The minimum volume;	Select the correct	
speaker	Check the recording	recording format;	
	format;		

	Confirm whether the	Connect the headset		
No sound from headphones	headset is connected	properly;		
	properly;	Adjust the volume;		
	The minimum volume;	Check whether audio or MP3		
	The damaged audio or	files are damaged, make		
	MP3 files caused the	sure the file integrity;		
	noise or no voice;			
Unable to	Check whether the USB	Ensure that no damage of		
	cable is damaged;	the USB connection;		
properly	Whether USB	Normal USB cabl		
upload/down	connection is normal;	connection;		
load the	Check whether there	Delete blank memory;		
audio file	are gaps in the			
	memory;			

Statement: Our company won't in charge of data missing caused by using the machine or repairing it. Therefore please back up on your own if there's important data in the machine.